

## Positek

Garanti: 12 ay  
 Bu ürüne ait Türkiye içi kapı teslim fiyat ve teslim süresi içeren teklifimizi almak için [info@yursat.com.tr](mailto:info@yursat.com.tr) e-posta adresine başvuru yapabilir ya da ayrıntılı bilgi için +90 224 240 03 04 numaralı telefonumuzdan bizlere ulaşabilirsiniz.  
**Positek** Markası, tedarik süresi için lütfen bizimle iletişime geçiniz.

*Firmamız Positek Türkiye Distribütörü veya temsilcisi değildir. Firmamız sipariş durumunda, belirtilen ürünlerde sadece Orjinal ve yeni ürün teklifi sunmaktadır. Bu sitede gösterilen Özel marka adları ve ticari markalar ilgili sahiplerinin mülkiyetindedir, talep durumunda kaldırılmaktadır.*



| Ürün                                                    | Açıklama                                                                                                                                                                                                                                                        |
|---------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <a href="#">BRAKE SENSOR POSITEK S115 STROKE-100 MM</a> |                                                                                                                                                                                                                                                                 |
| <a href="#">26655</a>                                   | P500.94EYL50Z239                                                                                                                                                                                                                                                |
| <a href="#">P752-150</a>                                |                                                                                                                                                                                                                                                                 |
| <a href="#">P500.50hjz204</a>                           | ROTARY INDUCTIVE POSITION SENSOR 4-20AM 12-28V                                                                                                                                                                                                                  |
| <a href="#">P811.200</a>                                |                                                                                                                                                                                                                                                                 |
| <a href="#">P603.100eyj</a>                             | Inductive tilt angle sensor - Measuring range: 0 ... 100 degrees - Output signal: 4 ... 20 mA, two-wire (code E) - Operating voltage: 18 ... 28 VDC - Electrical connection via plug, IP67, M12, Plug included - Further specifications according to data sheet |
| <a href="#">P909</a>                                    |                                                                                                                                                                                                                                                                 |
| <a href="#">P-502-15-B</a>                              |                                                                                                                                                                                                                                                                 |
| <a href="#">P500 Rotary Sensor</a>                      |                                                                                                                                                                                                                                                                 |
| <a href="#">P500.60ej</a>                               | inductive rotary encoder for DC operation - Measuring range 0 ... 60 degrees - Analog output 4 ... 20mA - Supply voltage 18 ... 28VDC - Linearity error $\leq \pm 0.25\%$ v. Ew. - electrical connection via plug                                               |
| <a href="#">Rips P500</a>                               |                                                                                                                                                                                                                                                                 |
| <a href="#">P797-11</a>                                 |                                                                                                                                                                                                                                                                 |
| <a href="#">P811-1000</a>                               |                                                                                                                                                                                                                                                                 |

